

VISTA-10SE



The Vista-10SE offers a new level of flexibility with superior security features, end user simplicity and powerful control.

With the Vista-10SE, you're limited only by your desires and imagination. With six zones and 5800 wireless zone expansion, the Vista-10SE is the industry's most economical and sophisticated control that can operate lights and appliances.

Dependable features to meet your most demanding installations:

- ◆ Six hardwired zones standard
- ◆ Expands to 22 total zones when using 5800 wireless
- ◆ Seven user codes
- ◆ Two-way downloading
- ◆ Supports up to four relays
- ◆ False alarm prevention features

End users will appreciate the easy-to-use convenience and control features of the Vista-10SE:

- ◆ Wireless remote control - the 5804 - a four-button, programmable wireless key or the 5804BD, a bi-directional programmable wireless key with system status feedback
- ◆ Single or dual button wireless personal panic: 5802MN and 5802MN2
- ◆ Home automation to activate lights, appliances, garage doors, and numerous other devices
- ◆ Vista Interactive Phone Module (VIP) that gives the end user control of their system from any touchtone phone; the 4285 VIP module responds in clear English, with over a 100 word vocabulary
- ◆ Full English display keypads for clear understanding of system status and zone locations
- ◆ Paging - openings, closings, alarm and trouble messages can be sent directly to a pager, allowing system status to be confirmed; parents can use this feature to verify that their children have arrived home
- ◆ Quick Exit enables users to leave the house for a brief time without disarming the system

VISTA-10SE

SPECIFICATIONS:

ELECTRICAL

- ◆ 500 mA, Aux - 12 VDC
- ◆ 16.5 VAC/25 VA transformer
- ◆ Alarm output 12 VDC, 2.0 amps max
- ◆ For UL installations, combined Aux and alarm output cannot exceed 600mA

OUTPUT CONTROL

- ◆ Supports one relay board (part number 4204) for four relays

ZONES

- ◆ Six hardwired zones
 - Selectable response: 10msec, 350msec, 750msec
 - Expandable to 22 zones using 5800 wireless
 - 16 zone types to choose from
 - Programmable swinger suppression

SUPPORTED DEVICES

Hardwired Expansion Devices

- ◆ 4204 supports up to four relays-15mA (each active relay draws 40mA)
- ◆ Keypads
 - 6139 custom English (required for programming) - 100mA
 - 6128 fixed English LCD - 85mA/40mA
- ◆ Voice module 4285 VIP - 160mA
- ◆ Four wire smoke detectors

WIRELESS RECEIVER SYSTEMS

- ◆ 5800 receivers
 - 5881L up to eight zones - 50mA
 - 5881M up to 16 zones - 50mA
- ◆ All receivers support
 - Diversity reception with two antennae
 - Remote mounting for best location
 - Unique supervision and low battery indications by point

TRANSMITTERS

- ◆ 5800 Series
 - Three volt Duracell lithium batteries
 - One mile range
 - Tamper is standard

AGENCY LISTINGS

- ◆ UL Residential Fire and Burglary and CFM

COMMUNICATIONS

- ◆ Touch tone or pulse
- ◆ Formats supported
 - ADEMCO Contact ID
 - ADEMCO 4 + 2 Express
 - ADEMCO low speed
 - SESCOA/Radionics
- ◆ 3 + 1, 4 + 1 and 4 + 2 reporting
- ◆ Reporting capabilities: Split, Dual, Split/Dual, Pager

Ordering Information

| Part No. | Description |
|------------|---------------|
| Vista-10SE | Control Panel |